

## 10. 2G~3.5G PDA/Mobile Phone Remote Access

The digital video/audio recorder can also be remotely accessed by using a web browser installed on a PDA or mobile phone that (1) supports **xHTML** and **MJPEG file format**, and (2) has screen resolution at **240x320** or above.

Please enter the domain name or IP address of the digital video/audio recorder in the Location/Address field of the web browser, and the remote login display will be shown. (For most of the mobile devices, the DVR will automatically redirect to the correct web page, Ex. <http://192.168.1.89/wap.htm> for IP address <http://192.168.1.89>. If not, please enter the full address with /wap.htm. The user may need to enter <http://192.168.1.89:800/wap.htm> if HTTP port has been changed to 800.)

Press this block to submit the content to the digital video/audio recorder. The new settings will take effect, and the screen will refresh.

Channel selection: Q1 = CH 1; Q2 = CH2, Q3 = CH3..... or 1 = full channel display.

Press this block to select **auto-refresh** frequencies 1second, 2 second, 3second.....  
Or press next key for updated images.



Alarm outputs 1-4 (unchecked for normal, checked for triggered). Administrator can check to trigger the alarm output, uncheck for back to normal.



Status indicators for alarm inputs 1-5 (top row), 6-10, and 11-16 (unchecked for normal, checked for alarm).

### Application:

- 1). As DVR is triggered forward an e-mail to mobile phone/PDA